




## Screw Ends Form

--Form 21 22

--Supported end



Form	Ball screw size					Thread undercut ring		
	d <sub>0</sub>	l	L1	D1	S	M1	w	Φz
21	8	2.5	28	6 <sup>-0.005</sup> <sub>-0.012</sub>	8	M6X0.75	1.5	5
	12	4/5/10	32	8 <sup>-0.005</sup> <sub>-0.012</sub>	10	M8X1	2	7
	12	4/5/10	36	10 <sup>-0.005</sup> <sub>-0.012</sub>	11	M10X1	2	8
	16	4/5/10/16	36	12 <sup>-0.005</sup> <sub>-0.012</sub>	11	M12X1	2	10
	20	4/5/10/20	47	15 <sup>-0.005</sup> <sub>-0.014</sub>	13	M15X1	2	13
	20	4/5/10/20	58	17 <sup>-0.005</sup> <sub>-0.014</sub>	15	M17X1	2	15
	25	4/5/10/25	62	20 <sup>-0.005</sup> <sub>-0.014</sub>	17	M20X1	2	18
	32	5/10/20/32	76	25 <sup>-0.005</sup> <sub>-0.014</sub>	20	M25X1.5	3	23
	40	5/10/20/40	72	30 <sup>-0.005</sup> <sub>-0.015</sub>	25	M30X1.5	3	28
	50	5/10/12/20/40	93	40 <sup>-0.005</sup> <sub>-0.015</sub>	35	M40X1.5	3	38
22	16	4/5/10/16	36	12 <sup>-0.005</sup> <sub>-0.012</sub>	11	M12X1	2	10
	20	4/5/10/20	47	15 <sup>-0.005</sup> <sub>-0.014</sub>	13	M15X1	2	13
	20	4/5/10/20	58	17 <sup>-0.005</sup> <sub>-0.014</sub>	15	M17X1	2	15
	25	4/5/10/25	62	20 <sup>-0.005</sup> <sub>-0.014</sub>	17	M20X1	2	18
	32	5/10/20/32	76	25 <sup>-0.005</sup> <sub>-0.014</sub>	20	M25X1.5	3	23
	40	5/10/20/40	72	30 <sup>-0.005</sup> <sub>-0.015</sub>	25	M30X1.5	3	28
	50	5/10/12/20/40	93	40 <sup>-0.005</sup> <sub>-0.015</sub>	35	M40X1.5	3	38



Unit : mm

Ball screw size		Keyway			End support block			
d <sub>0</sub>	l	S	b	t	FK	EK	AK	BK
8	2.5	-	-	-	FK06	EK06	-	-
12	4/5/10	-	-	-	FK08	EK08	-	-
12	4/5/10	-	-	-	FK10	EK10	AK10	-
16	4/5/10/16	-	-	-	FK12	EK12	AK12	-
20	4/5/10/20	-	-	-	FK15	EK15	AK15	-
20	4/5/10/20	-	-	-	FK17	-	-	-
25	4/5/10/25	-	-	-	FK20	EK20	AK20	-
32	5/10/20/32	-	-	-	FK25	-	-	-
40	5/10/20/40	-	-	-	FK30	-	-	BK30
50	5/10/12/20/40	-	-	-	-	-	-	BK40
16	4/5/10/16	11	4	2.5	FK12	EK12	AK12	-
20	4/5/10/20	13	5	3	FK15	EK15	AK15	-
20	4/5/10/20	15	5	3	FK17	-	-	-
25	4/5/10/25	17	6	3.5	FK20	EK20	AK20	-
32	5/10/20/32	20	6	3.5	FK25	-	-	-
40	5/10/20/40	25	8	4	FK30	-	-	BK30
50	5/10/12/20/40	35	8	4	-	-	-	BK40